

Nauticast A2 Class A AIS Transponder

The robust AIS solution for professional use, both SOLAS and Inland

Easy installation, full connectivity

Single-box design with integrated colour display for easy installation. RS232/RS422 interfaces (NMEA 0183) allow for integration with other ship systems. Pilot plug and USB connector located in front panel give easy access to static and dynamic data.

Reliable and future proof

The NAUTICAST A2 is regarded by many as the most reliable device in its class, exceeding all relevant specifications (IMO, ITU, IEC and CCNR). Built as SDR (software defined radio) it offers maximum capability for upgrades to future technical standards.



Other main features

- Weatherproof & compact design
- Pilot plug and USB located in front panel
- Quick software upgrade via USB

- SART alarm and test support
- Intuitive graphical user interface
- Languages EN, DE, NL, FR, HU, ES, RO

Nauticast GmbH

Lützowgasse 12-14 / 3.0G 1140 Vienna, Austria







Upgrade from other AIS to Nauticast A2

Choosing the right upgrade products saves time & money

| Upgrade | | Nauticast AIS | Saab R4 | SRT Class A/L3 Inland / Oceansat | |
|----------|----------------------------|---|--|---|--|
| from: | | | | | |
| Mounting | Flush | 100 1052 (Alu 320mm x 240mm) | for R4 display: 100 1060 (Alu 272mmx200mm) | 100 1061 (Nylon 250mm x 115mm) (or use: 100 1060) | |
| | Gimbal | 100 1006 or 100 1005 | | | |
| Data | Sensor 13 ECDIS LONG RANGE | 100 1008 (for all cases) | | | |
| | | 100 1004 (alternative if old connection box used) | 100 1015 | 100 1009 | |
| Antenna | VHF (BNC fem) | N fem to BNC male 100 1053 | - (as before) | UHF fem to BNC male 100 1050 | |
| Ante | GPS (TNC fem) | - (as before) | - (as before) | - (as before) | |





Specifications & Accessories

Technical Specifications

Model Nauticast A2

Size: 237x70x170 mm VHF: SDR Transceiver

Frequency 156-163 MHz

Weight: 2,20 kg Output power 1/12.5W (±1.5dB) Sensitivity < -111 dBm

Power: 24VDC (12VDC) Connection: BNC female 17W avg consumption,

24W (48W) peak GPS: 50 Channels Frequency: L1(1575.42 MHz)

Interfaces: 5 x RS422 / 1 x RS232 Update rate: 1 Hz

Interfaces: 5 x RS422 / 1 x RS232 Antenna feed: 5 V DC Connection: TNC female

1 x Digital In (e.g. Blue sign)

Alarm Relay / Pilot plug Accuracy: Position < 2.0 m DGPS (CEP)
Position < 2.5 m GPS (CEP)

Environmental: Protected (EC 60945-Ed.4) (SA off)

Display: 64.5*78 mm LED backlit TFT Sensitivity: Tracking -162 dBm Cold Start -148 dBm

320*240 resolution 450 cd/m² luminance

Upgrade cables

| Upgrade from: | Nauticast AIS (all cases) | Nauticast AIS (no ext. switch) | Nauticast AIS (connection box) | Saab R4 | SRT |
|-------------------|------------------------------|-----------------------------------|-----------------------------------|--------------|--------------|
| Group: | 100 1008 | 100 1008-1 | 100 1004 | 100 1015 | 100 1009 |
| Sensor 13 | \ | / | / | \checkmark | \checkmark |
| ECDIS | ✓ | / | ✓ | / | \checkmark |
| Long Range | ✓ | √ | √ | \checkmark | \checkmark |
| Pilot Port (ext.) | X 1) | X 1) | X 1) | X 1) | X 1) |
| RS232 | мил јошт А2 | × | × | Rollet | × |
| External Switch | ✓ | - | X 2) | x 2) | ✓ |
| Alarm out | X 3) | × 3) | X 3) | V | X 3) |
| Power | \checkmark | \checkmark | X 2) | X 2) | X 2) |

- 1) Pilot port is integrated in front hatch of Nauticast A2. In case the prior pilot port connection is needed, use Long Range or ECDIS port.
- 2) Reconnect External Switch and power with standard Nauticast A2 power cable.
- 3) An external alarm relay is necessary for a load with more than 140VDC or 1.5A (see detailed upgrade instructions).



Order Information

Box Content & Recommended Accessories

| Purpose | Description | Prod. No. |
|--|---|--|
| Box Content | Nauticast A2 device, power cable, printed installation & operation guides; USB-Stick with full documentation & firmware (optional: printed product manual 80p, Art.No. 1001001-2) | 100 1001 |
| Mounting | Standard mounting bracket Gimbal mounting bracket | 100 1005 100 1006 |
| Interface | Connection Box for A2 Data cable A2 for Connection Box 2m Data cable A2 with open ends (labelled individually) Alarm Relay for A2 | 100 1011 100 1013 100 1003 100 1010 |
| Upgrade (from previous Nauticast AIS SOLAS/Inland models or from Saab R4 or from SRT compatible devices) | Retro fit flush mount Alu (replacing Saab R4 devices) Retro fit flush mount Nylon (replacing SRT compatible models) Retro fit flush mount Nylon (replacing SRT compatible models) Set: Upgrade data cable incl. Blue Sign for Nauticast AIS | |
| GPS Antennas 1) | MA700 GPS antenna with 10m cable (TNC male) AT575-68 GPS antenna (without cable) plug: TNC female | 100 1020 300 1019 |
| VHF Antennas | VH-3200 VHF Whip antenna with 5m cable and mounting gear Procom CXL 2-1/I N | 100 1028 100 1035 |
| Combi Antennas | Comrod AC17 with splitter AC Marine VHF/GPS-2 with splitter | 100 1025 100 1027 |
| Antenna Mounts | Procom FLG Antenna Deck Mounting Kit G1"-11 Thread Mount Deck mount for standard GPS Antenna 1"-14 Standard Thread Pipe mounting Bracket stainl.steel 1"-14 Standard Thread GPS Antenna Mount Nylon 1"-14 Standard Thread | |
| Network | Nauticast W1 Serial (RS232/RS422/RS485) to Wifi Server (802.11.b/g/n). TCP and UDP mode. Access Point/Router incl. DHCP Server. Metal casing 68x90x28mm. 9-24VDC power incl. 1m power cable with open ends. | |

1) Note: AIS type appr<mark>oval</mark> requires operation in Solas or Inland mode with one of the certified GPS antennas (MA700 or AT575-68 or combi-antenna AC-Marine VHF/GPS-2). In compliance with the certifications the VHF antenna may be any technically equivalent marine VHF antenna.

Inquiries & Orders

sales@nauticast.com T +43 1 5237 237 - 400 F +43 1 5237 237 - 150

Nauticast A2 product sheet 17_09 Technical specifications subject to change without notice

